REKA

by LUMARK

ZIGBEE GATEWAY

User manual

GW006

Product description

This gateway is the control center of your connected home for Zigbee and Bluetooth devices. With the Smart Life app, add and reset devices, control them through third-party apps and create Zigbee and Bluetooth groups.



Specifications

Product	Zigbee Gateway
Brand	Lumark (Reka range)
Model	GW006
Power	5 V DC, 1 A (USB-C)
Temperature	-10 °C to +55 °C
Humidity	10% to 90% RH (non-condensing)
Technologies	2.4 GHz Wi-Fi, Zigbee 3.0, Bluetooth 5.0
Dimensions	60 × 60 × 15 mm
Net weight	About 33 g

Packing list

Gateway × 1 · USB-C cable × 1 · User manual × 1

Preparation

1. Download the "Smart Life" app (or "Tuya Smart") from Google Play or the App Store.
2. Open it and tap "Register" to create an account, or "Log in".
3. On your phone, turn on location and Bluetooth, and connect it to your 2.4 GHz Wi-Fi network.
4. Keep the phone close to the gateway during the whole pairing.

Installation

5. Plug in the gateway with the USB-C cable: both lights turn on. Press and hold the button for 8 seconds, release, then wait 10 to 20 seconds until the red light flashes.
6. In the app, tap "+" in the top right corner, then "Add Device".
   - Quick mode (Bluetooth on): tap the gateway icon that appears.
   - Manual mode (Bluetooth off): choose "compatibility mode (hotspot)" in the top right corner, connect to the indicated hotspot, then return to the app.
7. Follow the on-screen steps.

Indicator lights

- **Red light (Wi-Fi)**
  - Flashing: network configuration in progress (slow flashing).
  - Steady: gateway connected to the network.
  - Off: gateway not connected to the Internet.
- **Blue light (pairing)**
  - Flashing: pairing mode, Bluetooth or Zigbee devices being paired.
  - Steady: pairing finished, normal operation.

To reset: press and hold the button for 8 seconds, then pair again.

Precautions

- Indoor use only.
- USB mains adapter (not included): input 100–240 V AC, 50/60 Hz, output 5 V DC / 1.0 A.
- Keep away from water, humidity and heat. Do not disassemble; unplug before cleaning.
- Keep out of reach of young children. Use at least 20 cm away from the body.

CE Complies with Directives 2014/53/EU, 2014/30/EU and 2014/35/EU. Frequencies: 2400–2483.5 MHz. Max. power (Wi-Fi): 17.5 dBm.

FIND THE INSTALLATION STEPS, THE WI-FI CONNECTION AND THE APP PAIRING BY SCANNING THE QR CODE

IMPORTER
JUNOY – 9 rue Pierre Demours – 75017 Paris
contact@junoy.fr – www.junoy.fr

Reka is a range of the Lumark brand, owned by JUNOY. Made in PRC.

Do not dispose of this product with household waste: take it to a collection point for waste electrical and electronic equipment (WEEE).